

JBL KARAOKE SYSTEM

RMA-220 + RM-10



Professional Karaoke Amplifier RMA-220

Frequency Response (-3db)	MIC 20/20kHz,±3dB MUSIC 20/20kHz,±3dB
Maximum Output	200W+200W (RMA220)/ 250W+250W (RMA330)
Input sensitivity	MIC 6mV / 3.3KΩ DVD, TAPE, AUX 300mV / 47KΩ, BGM 300mV / 47KΩ
Output level Impedance	PRE OUT 2.2V / 2.2KΩ SUB OUT 2.2V / 2.2KΩ, REC OUT 300mV / 2.2KΩ MUSIC OUT 2.2V / 2.2KΩ
Key control range	Music 11 steps, ± 5 tones
Video input jack	Level/Impedance 1Vp-p/75ohm
Power Supply Others	Supply voltage 220V/240V 50/60Hz
Power consumption	650W (RMA220)/ 700W (RMA330)
Dimensions (HxWxD)	420 x 138 x 430 (RMA220-RMA330)
Weight	13.5kg

Professional Karaoke Speaker RM-10

Description	3-Speaker, 2 Way karaoke monitor
Max. Recommended Amplifier Power	175w
Power Handling (Continous/Peak)	50w/400w
Sensitivity	(2.83v/1m) 92db
Normal Impedance	8 Ohms
Crossover Frequencies	1,700 Hz
Low-Frequency Transducers	1 x 10" cones with high-temperature voice coil
High-Frequency Transducers	2 x 3" cones with high-temperature voice coil
Frequency Response (-3db)	40Hz - 20Khz
Dimensions	(HxWxD) 335mm x 530mm x 245mm
Weight	Per Speaker 13.5kg / 29.7lb