



#### TN-390

Features :  
 Digital Display  
 AM : 522-1620kHz  
 FM Stereo : 87.5-108MHz  
 Auto search tuning and  
 manual tuning  
 20 preset memories  
 (FM 10 and AM 10)

### Specifications

|                                  |                   |
|----------------------------------|-------------------|
| FM Tuner :                       |                   |
| .....Frequency Range :           | 87.5-108MHz       |
| .....Antenna Terminals :         | 75 ohm Unbalanced |
| .....30dB Sensitivity            | <10μV             |
| .....Frequency Response :        | 20Hz-15kHz +/-3dB |
| .....IF Rejection :              | >80dB             |
| .....Total Harmonic Distortion : | 1%                |
| .....Signal-to-noise Ratio :     | >50dB             |
| .....Stereo Separation 1kHz :    | >40dB             |
| AM Tuner :                       |                   |
| .....Frequency Range :           | 522-1620kHz       |
| .....Antenna Terminal :          | Loop Ant.         |
| .....20dB Sensitivity :          | <1mV              |
| .....Signal-to-noise Ratio :     | >35dB             |
| Dimensions (WxHxD) :             |                   |
| .....Exclude Mounting            | 432x78.5x280mm.   |
| .....Include Mounting            | 483x80x284mm.     |
| Power Requirement :              | 220Vac 50Hz 5VA   |
| Weight :                         | 4kg/8.8lbs        |